

PORTABLE SOLAR PANEL

SOLARSAGA



Harness the power of the sun with the **Jackery SolarSaga 100W Solar Panel**. Lightweight and portable for on-the-go power from the sun. Charge your Explorer with the **SolarSaga** and simultaneously power your devices - and enjoy a continuous supply of power.








- ☑ 100W MONOCRYSTALLINE SOLAR PANEL
- ☑ HIGH CONVERSION EFFICIENCY UP TO 23%
- ☑ LIGHTWEIGHT & DURABLE
- ☑ BUILT-IN KICKSTAND
- ☑ 1x USB-C OUTPUT PORT, 1x USB-A OUTPUT PORT
- ☑ FOLDABLE WITH EASY CARRY HANDLE

Jackery

PORTABLE POWER STATIONS

HARVEST SOLAR ENERGY TO CHARGE YOUR SMARTPHONES AND JACKERY PORTABLE POWER STATIONS

SPECIFICATIONS

 Wattage	 Cell Efficiency	 Weight	 Max Power Voltage (Vmp)	 Open Circuit Voltage (Voc)	 Operating Temperature	 USB Ports
100W	23%	4.69kg	18V = 5.55A	21.6V = 6A	-10°C to 65°C	USB-A Outlet: 1 x USB-A (5V, 2.4A) USB-C Outlet: 1 x USB-C (5V, 3A)

DIMENSIONS



FOLDED 61 x 53 x 2cm • UNFOLDED 122 x 53 x 4.5cm



CHARGE TIMES

DIRECT SUNLIGHT, PERFECT CONDITIONS



Jackery 250
full charge time: **4 Hours**



Jackery 500
full charge time: **8 Hours**

Jackery
PORTABLE POWER STATIONS